

## **SLIM AND COMPACT RELAY** FOR WIDER APPLICATIONS



## **FEATURES**

Slim and compact size

20% more compact (width and height) than existing model\* (with the condition of screw terminal socket for DIN rail) \*Compared with our HJ relay.

· High reliability and reasonable price Uses gold-flashed contacts for highly reliable contact.

· Environmentally friendly

0.53W 0.9VA

In consideration of the environment, cadmium-free contacts are used. Also supports lead-free.

(Both relays and screw terminal socket.)

Characteristics

### · Slim screw terminal socket

**HN RELAYS** 

(AHN)

Utilizes relay-securing hook for easy relay removal.

## **TYPICAL APPLICATIONS**

**Control panels** Machine tools Forming machines **Commercial equipment Agricultural machines** Vending machines

## SPECIFICATIONS

#### Contacts

Contact arrang	gement	2 Form C		
	resistance, max. op 6 V DC 1 A)	$50 m\Omega$		
Contact mater	ial	Gold-flashed silver alloy		
	Nominal switching capacity	5A 250V AC, 5A 30V DC		
Rating (resistive load)	Max. switching power	1,250 VA, 150W		
	Max. switching voltage	250V AC, 30V DC		
	Max. switching current	5 A		
	Min. switching current*9	1V 1 mA		
Expected life	Mechanical (at 300 cpm)	AC: 10 <sup>7</sup> DC: 2×10 <sup>7</sup>		
(min. operations)	Electrical (at 20 cpm) (resistive load)	10 <sup>5</sup>		

#### Coil

Nominal operating power

#### Remarks

- Specifications will vary with foreign standards certification ratings. \*1
- Measurement at same location as "Initial breakdown voltage" section
- \*2 Detection current: 10mA
- \*3 Excluding contact bounce time
- \*4 For the AC coil types, the operate/release time will differ depending on the phase.
- $^{\star 5}$  Half-wave pulse of sine wave: 11ms; detection time: 10  $\mu s$
- \*6 Half-wave pulse of sine wave: 6ms \*7 Detection time: 10us
- \*8 Refer to 6. Conditions for operation, transport and storage mentioned in AMBIENT ENVIRONMENT.
- \*9 This value can change due to the switching frequency, environmental conditions and desired reliability level, therefore it is recommended to check this with the actual load.

Unaracteri	31103			
Max. operat	ing speed	20 cpm (at max. rating)		
Initial insula	tion resistanc	Min. 1,000 MΩ at 500 V DC		
Initial	Between open contacts		1,000 Vrms for 1 min.	
breakdown	Between cor	ntact sets	3,000 Vrms for 1 min.	
voltage*2	Between cor	ntact and coil	5,000 Vrms for 1 min.	
Operate tim	e*3 (at nomina	al voltage)	Max. 15 ms*4	
Release time (without diode)*3 (at nominal voltage)			Max. 10 ms*4	
Temperature rise, max. (at 70°C) (at nominal voltage)			60°C	
Shock resistance		Functional*5	Min. 100 m/s <sup>2</sup> {10 G}	
		Destructive*6	Min. 1,000 m/s <sup>2</sup> {100 G}	
Vibration resistance		Functional*7	10 to 55 Hz at double amplitude of 1.5 mm	
		Destructive	10 to 55 Hz at double amplitude of 1.5 mm	
Conditions for operation, transport and storage*8 (Not freezing and condensing at low temperature)		Ambient temp.	<b>−40°C to +70°C</b> −40°F to +158°F	
		Humidity	5 to 85% R.H.	
Unit weight			Approx. 19g .67 oz	

# ORDERING INFORMATION

Ex. AHN					
Contact arrangement	Terminal arrangement	Type classification	Coil voltage		
2: 2 Form C     1: AC plug-in type     0: Standard     05: 5, 06: 6, 12: 12, 24: 24, 48: 48       2: DC plug-in type     0: Standard     X0: 100/110 V AC, 100 V DC       2: With diode     X1: 110/120 V AC, 110 V DC       3: With LED indication, diode     Y0: 200/220 V AC, Y2: 220/240 V					

Note: Products conform to UL/C-UL and VDE, as standard (VDE pending).



# TYPES

### 1. Plug-in type

	2 Form C		
Coil voltage	Part No.		
5V DC	AHN22005		
6V DC	AHN22006		
12V DC	AHN22012		
24V DC	AHN22024		
48V DC	AHN22048		
100V DC	AHN220X0		
110V DC	AHN220X1		
12V AC	AHN21012		
24V AC	AHN21024		
100/110V AC	AHN210X0		
110/120V AC	AHN210X1		
200/220V AC	AHN210Y0		
220/240V AC	AHN210Y2		

-			
Ceilveltage	2 Form C		
Coil voltage	Part No.		
5V DC	AHN22105		
6V DC	AHN22106		
12V DC	AHN22112		
24V DC	AHN22124		
48V DC	AHN22148		
100V DC	AHN221X0		
110V DC	AHN221X1		
12V AC	AHN21112		
24V AC	AHN21124		
100/110V AC	AHN211X0		
110/120V AC	AHN211X1		
200/220V AC	AHN211Y0		
220/240V AC	AHN211Y2		

Note: Packing quantity; Inner carton: 50 pcs, Outer carton: 500 pcs.

#### 3. Plug-in with diode type

5 71	
	2 Form C
Coil voltage	Part No.
5V DC	AHN22205
6V DC	AHN22206
12V DC	AHN22212
24V DC	AHN22224
48V DC	AHN22248
100V DC	AHN222X0
110V DC	AHN222X1

Note: Packing quantity; Inner carton: 50 pcs, Outer carton: 500 pcs.

Note: Packing quantity; Inner carton: 50 pcs, Outer carton: 500 pcs.

#### 4. Plug-in with diode and LED indication type

2. Plug-in with LED indication type

-			
Coil voltage	2 Form C		
Convoltage	Part No.		
5V DC	AHN22305		
6V DC	AHN22306		
12V DC	AHN22312		
24V DC	AHN22324		
48V DC	AHN22348		
100V DC	AHN223X0		
110V DC	AHN223X1		

Note: Packing quantity; Inner carton: 50 pcs, Outer carton: 500 pcs.

#### 5. Screw terminal socket

Туре	No. of channels	Item	Part No.
For DIN rail assembly	2 channels	HN2 screw terminal socket	AHNA21

Notes) 1. Packing quantity: 10pcs. (Inner carton), 100pcs. (Outer carton)

2. Products conform to UL, C-UL, as standard.

In order to prevent breakage and disfiguring, the screw tightening torque for the terminal socket should be within the range of 0.5 to 0.8 N·m.
When attaching directly to a chassis, please use an M3 × 16 metric coarse screw thread.

5. To prevent damage and deformity, please use the relay-securing hook at 10 N or less.

# COIL DATA (at 20°C 68°F)

### DC coils

Coil voltage V DC	Pick-up voltage, V DC (max.) (Initial)	Drop-out voltage, V DC (min.) (Initial)	Nominal coil current, mA (±20%)	Coil resistance, Ω (±10%)	Nominal operating power, W	Max. allowable voltage, V DC
5	3.5	0.5	105.9	47		8.5
6	4.2	0.6	88.4	68		10.2
12	8.4	0.12	44.2	270		20.4
24	16.8	0.24	22.1	1,090	0.53	40.8
48	33.6	0.48	11	4,350		81.6
100	70	10	5.3	18,870		170
110	77	11	4.8	22,830		187

### AC coils (50/60Hz)

Coil voltage Pick-up voltage V AC (max.)				Nominal coil current, mA (±20%)		Nominal operating power, VA	
V AC	(Initial)	(Initial)	50Hz	60Hz	50Hz	60Hz	voltage, V AC
12	9.6	3.6	93	75			16.8
24	19.2	7.2	46.5	37.5			33.6
100/110	80/88	30/33	11.0/13.0	9.0/10.6	Approx.	Approx.	140/154
110/120	88/96	33/36	10.0/11.8	8.2/9.7	1.1 to 1.4	0.9 to 1.2	154/168
200/220	160/176	60/66	5.5/6.5	4.5/5.3			280/308
220/240	176/192	66/72	5.0/5.9	4.1/4.8			308/336


# HN (AHN)


# DIMENSIONS

### 1. Plug-in type 2 Form C



2.6






1 to 3mm .039 to .118 inch: ±0.2 ±.008


**Tolerance** 


±0.1 ±.004

 $\pm 0.3 \pm .012$ 



Schematic (Bottom view)






	<b>6 5 5</b>
With Diode a	and LED type

### 2. Screw terminal socket






Dimension :


Max. 1mm .039 inch:


Min. 3mm .118 inch:

\* Reference in case of using DIN rail (ATA48011)

# Schematic (Top view)









## **REFERENCE DATA**


1. Max. switching capacity



2-(1). Coil temperature rise (AC type) Measured portion: Inside the coil Ambient temperature: 23°C 73°F



2-(2). Coil temperature rise (DC type) Measured portion: Inside the coil Ambient temperature: 30°C 86°F




All Rights Reserved © COPYRIGHT Matsushita Electric Works, Ltd.

mm inch


## NOTES

### 1. About the relay-securing hook

1) Installation of the securing hook is easily performed by pressing upward in the direction of the arrows.



2) Removal of the securing hook is easily performed by releasing the hook and pressing down, as shown in the figure.



2. Diode characteristics

1) Reverse breakdown voltage: 90V (5 to 48V DC type)

250V (100, 110V DC type)

## 3. Diode type

Since the diode inside the relay coil are designed to absorb the counter emf, the element may be damaged if a large surge, etc., is applied to the diode. If there is the possibility of a large surge voltage from the outside, please implement measures to absorb it.

For Cautions for Use, see Relay Technical Information.